

VENUCAST™

Aria Aura

Auracast Headphones
for Public Spaces



Interactive User Guide

Version 2.4



Start Listening



Activate Free
24-Month Warranty

< Back



Main Menu

1. Join Your Kit Broadcast

2. Search or Switch Broadcasts

3. Buttons & Indicators

4. Power & Charging

5. Troubleshooting

6. Register & Support

Next

1. Join Your Kit Broadcast

Aria Aura works as an add-on to your kit, e.g. [AuraPlex H4](#).



Turn your headphones **ON**.

→ LED blinks **orange**. (Searching for a nearby broadcast)

✓ **Joined:** LED turns **solid orange**.



Next



2. Search or Switch Broadcasts

To hear a different broadcast:

❶ Slide the power switch to **ON**.

❷ Hold  for 5s → LED blinks **orange**.

✓ **Joined:** LED turns **solid orange**.





Multiple broadcasts nearby?



Hold  again to scan the next broadcast. Repeat until you find the one you want.

Next



3. Buttons & Indicators



A LED

- Solid orange → Joined a broadcast
- Blinking orange → Searching broadcasts


Multi-Function Button

- Search/Switch broadcasts
-

EQ Button


- Voice Clear 1/2 & Bass & Balance

Next



4. Power & Charging

- **USB-C** power: 5V, 1-2.4A
- Charging: LED stays **solid red**.
- Fully charged: LED turns **off** (~2.5h).
- Playtime: Up to 35 hours.

[Next](#)

< Back




Menu

Rate This Guide

Your feedback helps us improve this guide for everyone.

It only takes a moment.



Next


5. Troubleshooting

- No sound or not joined?
→ Hold   for 5s.



- Need to join a secured broadcast?
→ [Contact support](#)

Next



6. Register & Support

Register Your Product

Extended warranty & get updates.

Get 24M Warranty

Need help? Contact Us



Email

support@venucast.com



Call



USA (Toll Free)

+1 888 464 0168



Other Regions



Chat

